


LED 4*100W COB Blinder Light IM-AL04100



User Manual

Please read over this manual before operation light

1. Display Parts:



- A. Functionkey
- B. Up key
- C. Down key
- D. Enter key

Operate introduce: Press function key “A” will circulate seven different function effects, The line of words upside LCD stand for the present working function (please refer to the function table.), the under line stands for LCD shows what address code or speed parameter of this function is at.

2. LCD display window functions comparison (Press D key to confirm after choosing certain function)

Item	Display	Function
1	A001	6 CH Mode, B、 C Key change 001-512
2	D001	12 CH Mode, B、 C Key change 001-512
3	H001	2 CH Mode B、 C Key change 001-512
4	CC00	Auto run mode 00-10, B, C change 00-10
5	LL00	Auto run mode Speed 01-99, B, C change 01-99
6	CP00	Auto run mode 2, B, C change speed from 01-99
7	DE00	Auto Run Mode 3
8	bEb1	Voice Mode
9	W255	White, (000—255) B、 C Change brightness
10	Y255	Warm White, (000—255) B、 C Change brightness
11	n255	Strobe, (000—255) B、 C Change Speed

3.DMX512 2CH Description

Item	Function	Description
1CH	W Dimmer	Dimmer from dark to bright
2CH	Y Dimmer	Dimmer from dark to bright

4. DMX512 6 CH Description

Item	Function	Description
1CH	Dimmer	Dimmer from dark to bright
2CH	Strobe	From slow to fast

3CH	Function	0-25 , nothing 26-35:jump run 1 126-135: jump run 11 136-145: gradually run 1 236-245: gradually run 11 246-255: Voice mode
4CH	Function speed	From slow to fast
5CH	W Dimmer	Dimmer from dark to bright
6CH	Y Dimmer	Dimmer from dark to bright

5.DMX512 12 CH Description

Item	Function	Description
1CH	Dimmer	Dimmer From dark to bright
2CH	Strobe	Strobe From slow to fast
3CH	Function	0-25 , nothing 26-35:jump run 1 126-135: jump run 11 136-145: gradually run 1 236-245: gradually run 11 246-255: Voice mode
4CH	Function speed	From slow to fast
5CH	W1 Dimmer	W1 Dimmer From dark to bright
6CH	Y1 Dimmer	Y1 Dimmer From dark to bright
7CH	W2 Dimmer	W2 Dimmer From dark to bright
8CH	Y2 Dimmer	Y2 Dimmer From dark to bright
9CH	W3 Dimmer	W3 Dimmer From dark to bright
10CH	Y3 Dimmer	Y3 Dimmer From dark to bright
11CH	W4 Dimmer	W4 Dimmer From dark to bright
12CH	Y4 Dimmer	Y4 Dimmer From dark to bright

6. Function Trait:

Simple operation, humanized design, light-dimmer without twinkle or twitter. It can be used for video camera, photograph, TV station etc. occasion where strictly to light.